

AS Series LED 2-Line Sign OTA Configuration (Quick Setup)

* Calculated Value, See Manual or	Check notes at Bottom of Page for Quick Reference.		
ITEM	NOTES	DEFAULT	OTA COMMAND
			(Send as a Page ONLY what is Written in Black)
Frequency	Supplied by Customer		N/A - Use Programming Software
Protocol	FLEX/POCSAG		N/A - Use Programming Software
Cap Code(s)	Up to 6 Total (POCSAG) or 16 (Flex)		N/A - Use Programming Software
Sign Type	* First OTA Command (1-Line or 2-Line Sign Model)	2	GALEDTYPE=2
Mail Drop Cap Code(s)	Newsfeed (Normally NOT Used)	None	GALEDMDCAP=XXXXXX* (See Top)
Priority Msg Cap Code(s) * *	* Specified by Customer, normally All On (FFFFFF)	FFFFFF	GALEDPRICAP=XXXXXX** (See Bottom)
Timer Display	* Default is Usually Turned OFF	OFF	GALEDTM=OFF
Timer Date On/Off	* Default is Usually Turned OFF	OFF	GALEDDT=OFF
Timer Date Setting	Default is Usually NOT Used		GALEDDATE=YMMDD* (See Top)
Timer Date Mode	MM DD, YY (Default is Usually NOT Used)	1	GALEDDTMD=1
Timer Time Setting	24 hr Clock (Set ONLY when Timer is Active)		GALEDTIME=HHmmSS* (See Top)
Timer Month Language	English (Set ONLY when Timer is Active)	ENG	GALEDLANG=ENG
Buzzer On/Off	* Default is Turned ON	ON	GALEDBZ=ON
Buzzer On Time	* 1 Second	001	GALEDBZTM=001
Buzzer Music Type	* Type 0 = Solid Tone	0	GALEDBZTY=0
Default Message ***	* BLANK (If not Specified by Customer)		GALEDMSG=
Message Counter	* Automatic	AU	GALEDMGCT=AU
Auto Clear Delay Time	* 5 Minutes (Unless Specified by Customer)	300	GALEDCLRDY=300
Auto Clear Count Times	* Normally NOT Used (Unless Specified by Customer)	000	GALEDCLRCT=000
Clear by Reset	* RESET (Prefix or Suffix) (Normally ON) ALWAYS	ON	GALEDRESCM=ON
Time Stamp Mode	* 0=OFF (Usually NOT Used)	0	GALEDTMSM=0
Appear Message Mode	* Hold	7	GALEDAPPM=7
Disappear Message Mode	* Instant	A	GALEDDISM=A
Priority Message	* Support Both Priority Msg and Priority Msg Cap Code	4	GALEDPRIM=4
Priority Msg Relay "ON" Time	* 10 Seconds (How Long the Relay will Stay Active)	010	GALEDRLYTM=010
Mail Drop Time Out OFF	* No Timeouts of Mail Drop	ON	GALEDMDTOOF=ON
Priority Message Counter	* 1 to 5 (Default 5)	5	GALEDPRICT=5
Priority Message Clear	* Support Clear Command (Normally ON)	ON	GALEDPRICLR=ON
Automatic Message Counter	* 1 to 24 (Default 24)	24	GALEDAUCT=24
Priority Msg Auto Clear Delay Time	* 3 Minutes (Unless Specified by Customer)	180	GALEDPCLRDY=180

* **Priority Cap Codes: 0=Non-Priority and F=Priority** (For Each Cap Code Slot) **For Instance:** Cap codes 1,3 and 5 **are Priority** and Cap Codes 2, 4 and 6 are **not** Priority, then the OTA Command would be **GALEDPRICAP=F0F0F0**. *** This is the Message that shows when no other Messages are being displayed.
NOTE: 911 Prefix is used for Non-Priority Cap codes and a "**Priority Message**" has to be "**sent**" in order for the **Relay** to work, if the Relay is activated.