

Bravo Br-502 Numeric Pager



"Your Source for Pagers"

Visit Our Website at:

www.WirelessMessaging.com

NOTE: Frequency Required when Ordered



P/N= 160-UPA for UHF (452-456)

P/N= 160-UPB for UHF (456-459)

P/N= 160-UPC for UHF (460-463)

P/N= 160-UPD for UHF (464-469)

P/N= 160-VPC for VHF (153-158)

Features:

- Back-Light / Top Display
- Date and Time Display
- Pager Programming: PC Software Only (Sold Separately)
- Alert Modes: Chirp, Vibration, Vibration / Chirp, Melody and Silent
- Memory Backup (when Replacing Battery)
- Message Protect: Lock 10 Messages
- Out of Range Indicator and Alert
- Low Battery Indicator and Alert
- Message Slots: 18 Personal
- Delete Messages: All Messages or One Message
- Duplicate Message Indicator
- Error Message Indicator
- Unread Message Reminder Alert
- Message Time and Date Stamping

Specifications:

- Model: Br-502
- Frequency: 452-468 MHz, 135-175 MHz and 929-932 MHz
- Paging Sensitivity: -107dbm for UHF / VHF / 900 MHz
- Pager Baud Rate: 512 / 1200 / 2400bps for POCSAG
- Channel Spacing: 25 KHz Wide Band (WB)
- Code Format: POCSAG
- Receiver Type: Synthesized
- Alert Tone Loudness: 75db @ 12 inches
- Cap Codes: 6 Cap Codes for POCSAG
- Frequency Deviation: ± 4.5 KHz
- EIA Spurious: 50 db
- EIA Selectivity: 55 db @ ± 25 KHz
- IM Rejection: 50 db
- Operating Temperature: -10° C to 50° C
- Power Supply: 1 "AA" Alkaline Battery
- Weight with Battery: 45 grams
- Dimensions: 43 x 64 x 19.5 mm