

Bravo Br-802 Alphanumeric Pager



"Your Source for Pagers"

Visit Our Website at:

www.WirelessMessaging.com

NOTE: Frequency Required when Ordered



P/N= 162-UPA for UHF (452-455)

P/N= 162-UPB for UHF (456-459)

P/N= 162-UPC for UHF (460-463)

P/N= 162-UPD for UHF (464-469)

P/N= 162-VPC for VHF (153-158)

Features:

- 4-Line Alphanumeric Display (20 Characters per Line)
- Zoom from 4-Line to 2-Line Display
- Adjustable LCD Contrast / EL Backlight
- Time and Date Display / Stamping
- Pager Programming: PC Software Only (Sold Separately)
- 1 Daily Alarm
- Reminder Alerts: Unread Message and Low Battery
- Alert Modes: Vibrate, 8 Pleasing, Vibrate and then Audible or Silent (No Alert)
- 4 Selectable Alert Durations: 8 / 16 / 40 Seconds or Continuous – Selected by PC Software Only
- 3 Selectable Alert Modes: All Alert, Audio Only, Vibrate / Sleep – Selected by PC Software Only
- Tone Message - Selected by PC Software Only
- Indicators: Out of Range, Battery Level, Continuous Message
- Up to 40 Inbox Message Slots / Up to 40 Info Slots
- Protect Message: Up to 20 Inbox / 20 Saved Messages

Specifications:

- Model: Br-802
- Frequency: 452-468 MHz, 135-175 MHz and 929-932 MHz
- Paging Sensitivity: -107dbm for UHF / VHF / 900 MHz
- Pager Baud Rate: 512 / 1200 / 2400bps for POCSAG
- Channel Spacing: 25 KHz Wide Band (WB)
- Code Format: POCSAG
- Receiver Type: Synthesized
- Alert Tone Loudness: 75db @ 12 inches
- Cap Codes: 6 Cap Codes for POCSAG
- Frequency Deviation: \pm 4.5 KHz
- EIA Spurious: 50 db
- EIA Selectivity: 55 db @ \pm 25 KHz
- IM Rejection: 50 db
- Operating Temperature: -10° C to 50° C
- Power Supply: 1 "AA" Alkaline Battery
- Weight with Battery: 65 grams
- Dimensions: 80 x 54 x 19 mm