

WaveWare 2-Line Wallpager

Model: AS-112R



“Enhancing Mobile Alert Response”

P/N= **AS112R**

Visit Our Website at:

With Built-In Relay

www.WirelessMessaging.com

“Works Like a Pocket Pager”!

2630 National Dr. Garland TX. 75041 Ph: 1.800.373.1466

Also Available in 20-50 Characters - (Model: AS-122R)

Features:

- Alphanumeric LED Display
- Displays Exactly what your Pager Receives - No Special Formatting Required
- 1 or 2 Line Operational Mode (Specify when Ordering)
- 1-Line Mode: Displays Approx. 10-12 Characters Scrolls from Right to Left for Longer Messages
- 2-Line Mode: Displays Approx. 22-24 Characters Scrolls from Right to Left for Longer Messages
- Messages are Received Wirelessly from On-Site Paging System or from Wide Area Paging Service
- Messages are Automatically Manages for up to 24 Active Messages
- Message Time-Out Option using either Run-Time or Message Display Count as Time-Out Triggers
- Real-Time Clock with Message Stamping Option
- Priority Message Stacking for up to 5 Priority Messages
- Priority Message By Prefix (911)
- Message Clearing Feature using “Reset” by Prefix / Suffix
- Frequency, Cap Codes and Pager Baud Rate Programmed by way of PC Software.
- All Options and Features are Set by OTA Commands
- Program Software and Over-the-Air Commands (OTA) CD
- Delete All Messages by way of Over-the-Air Command
- Programmable Default Message (Up to 50 Characters)
- Wall Mount Bracket Kit Included
- Back to Back Signs Ceiling Hanging Kit Available
P/N= AS Brackets

Additional Features:

- Built-in Relay for use with Annunciators to get the Attention of Personnel for Important Priority Messages (Relay Harness is an Optional - Separate Purchase)
Relay Harness PN= AS Relay Cable
- 5 Priority Messages can be used to Activate the Relay using Key Strings of up to 20 Characters Embedded into each Priority Message
- Relay Activation by - 5 Priority Messages and / or by Priority Cap Code (Up to 6 Cap Codes)
- Horn / Strobe Combo Annunciator Option for use with the Built-in Relay – **Horn / Strobe Combo P/N= 0601-0118**

Specifications:

- Model: AS-112R Alpha Sign (WaveWare Wallpager)
- Case: Dark Aluminum with Red Display
- Frequency: 408-473 MHz, 138-174 MHz and 929-931 MHz
- RF Data Rate: 512 / 1200 / 2400bps for POCSAG, 1600 / 3200 / 6400bps for FLEX
- Channel Spacing: 25 KHz (WB) or 12.5KHZ (NB)
- Code Format: POCSAG or Flex
- Cap Codes: 6 Cap Codes (For POCSAG)
- LED Array: 160 x 16
- Red Characters: Approx. 10 / 4” Tall (One-Line) or Approx. 22 / 2” Tall (Two-Line)
- Dimensions: Case - 28” L x 6” H x 3” D
- Weight: Approx – 13 Lbs.
- Power: 110VAC (6Ft. Cord attached with 2 Prong Plug)