

# Apollo 2-Tone Voice Pager with Charger



- ✓ 2-Tone Voice
- ✓ Single Frequency
- ✓ Tone or Vibrate Alert
- ✓ Voice Storage Option



## Features:

- 2 Tone Decoding Format
- Six call per channel / 4 individual, 2 group call  
Same as Minitor 4
- All Cap Codes can be set as different tone alert types
- 120 seconds of Stored Memory (Option):  
Up to 4-30 sec Messages
- Loud clear voice level:  
85 DBA at 12 inches distance.
- Large volume control knob
- Slide switch with On/off , vibrate ,alert selection
- Tone & Vibrate alert
- Priority alert programmable
- Monitor channel function
- Audio lock on
- Monitor with carrier squelch
- Battery:  
One AA Ni-HM or Ni-Cad rechargeable battery or one AA alkaline battery
- Charger:  
Desk type charger as standard
- Fixed Alert volume:  
Programmable
- Battery low indicator:  
Special beep tone
- External Earphone Jack
- Heavy Duty Rugged housing , Strong Belt clip
- Reminder tone and LED Reminder flash
- 2 Status LED :  
Red LED light , flash when alert , LED on with unread voice,  
Green LED blinks with monitor ON  
Audio lock on Green LED ON
- RESET :  
Manual reset
- Auto reset revert with SQL, with program reset delay
- PTL option:  
Push to listen feature
- Disable Power OFF:  
By programming
- Disable Vibrate:  
By programming
- One channel:  
Synthesized or Crystal type receiver
- Frequency Band:  
VHF 143~174MHz, UHF 406~512 MHz.
- Band Type:  
Narrow band (12.5) & wide band (25.0)
- Two channel option in the future