

Apollo Pilot XP Alphanumeric Pager



"Your Source for Pagers"

Visit Our Website at:

www.WirelessMessaging.com



P/N= **Pilot- 460- XP**

Key Features:

- Meets IP-54 Approval
- Water Repellant and Dust Proof
- Loud Buzzer / Strong Vibrator
- 6 Keys of Operation / User Friendly Interface
- Program by PC Software or by Hand thru the Buttons
- Supported Languages: English, Spanish, Portuguese, Russian, German and French.

Specifications:

- Model: AL-A28 (Also called the Pilot XP)
- Frequency: 408-473 MHz, 138-174 MHz and 929-931 MHz
- Paging Sensitivity: POC 512bps - 5 μ V/M, 1200bps - 7 μ V/M
- EIA Selectivity: 60 dB \pm 25 KHz
- Spurious Rejection: 55db Below Carrier
- Image Rejection: 50db Below Carrier
- Frequency Stability: 7ppm of Reference Frequency Form -10 to 50C (+25 C ref.), 10ppm for VHF
- Pager Baud Rate: 512 / 1200 / 2400bps for POCSAG,
- Channel Spacing: 25 KHz (WB) or 12.5 KHz (NB)
- Code Format: 31 / 21 POCSAG (CCIR Code #1)
- Alert Tone Loudness: 85db @ 10 cm
- Cap Codes: 8 Cap Codes for POCSAG
- Dimension: 80(L) x 53(W) x 20(H) mm
- Weight: Approx. 56.5 Grams without Battery

Features:

- 4-Lines Total 84 Alphanumeric One Page Display
- Synthesized or Crystal Type
- Blue Backlight / Large LCD Display
- 8 Cap Codes for POCSAG
- 16 Memory Slots, 10 Sets of Full Message
- Large Memory Size: Total Capacity 262,144 Letters
- General Message: 16 Sets+ w/ Total Capacity 20,480 Letters
- 10 Personal Message Sets: Total Capacity 10,000 Letters
- Mail Drop: 15 Sets w/Total Capacity 228,345 Letters
- 4 Beeps Alerts w/LED Flash, 10 Melody Alerts w/LED Flash, Vibration w/ LED Flash, LED Flash Only or Sleep
- Selectable 12 Hr. or 24 Hr. Real Time Clock Format
- Manual Pager On / Off
- 5 Daily Alarm Sets, Auto Scroll and Zoom In / Out
- 10 Message Locks
- Real Time Clock Calendar
- Error, Duplicate and Full Message Indicators
- Message Time Stamp
- Month, Date, Year and Time Display
- Selective Message Lock / Delete
- Unread Message Reminder Alert
- "AAA" Rechargeable Battery
- Desktop Charger Included / Quick Charge

NOTE: Frequency Required when Ordered