## **Apollo WP-100 Wrist Pager**



"Enhancing Mobile Alert Response"

"Your Source for Pagers"

Visit Our Website at:

www.WirelessMessaging.com



P/N= WP-100 UHF (460-470)

**NOTE:** Frequency Required when Ordering

## Features:

- POCSAG Coding Format
- 1.54 inch Touch Screen
- 6 Cap Codes
- 10 Message Storage
- Charging / Programming via Micro USB
- Beeping Alarm, Vibration and Silent Mode
- 3 Brightness Levels on Backlit
- 3 Sound Levels
- Auto Scroll
- 2 Alarm Clocks
- Water Resistant Only (NOT Water Proof)
- 7 Days of Standby Time
- Antenna inside the Wrist Band

## Specifications:

- Model: WP-100
- Frequency: 430 470 MHz
- Paging Sensitivity: 512bps -5V/M, 1200bps -7V/M and 2400bps - 9V/M
- Pager Baud Rate: 512 / 1200 / 2400bps for POCSAG
- Channel Spacing: 12.5 KHz (NB) 25 KHz (WB)
- Code Format: POCSAG (Alphanumeric)
- Adjacent Channel: 50dBc @ 12.5KHz and 25KHz
- Cap Codes: 6 Cap Codes for POCSAG
- Spurious Rejection: 50dB Below Carrier
- Battery: Rechargeable LIPO Battery 3.8v 400mAh
- Weight with Battery: 44g
- Dimensions: 853(L) x 42(W) x 15(H) mm





## **WP-100**

The Wrist-Worn Receiver WP-100 is Capable of Receiving Notifications in Alphanumeric Messages. Made with a Compact Size, it is Equipped with a Side Button and a 1.54-inch Color Touch Screen.

The Charging and Programming can be Easily Done via Micro USB Cable and the Inbox can Store up to 10 Messages in 300 characters Each for Quick Review.

WaveWare Technologies, Inc. 1.800.373.1466 Sales@WirelessMessaging.com

9.22.21